

Midland G6 XT

PMR446 Transceiver



uk

Cod. C830.08

G6 XT is the first small and practical device that can operate in **2 different Working mode**: in **Standard mode** with all the functions of a traditional PMR446 transceiver, or in **Baby Sitter mode** with only the specific function for the baby monitor use enabled.

G6 XT can be used as standard radio with all the traditional, reliable and practical functions of a PMR446 transceiver, or just as Baby Monitor with the specific "Baby Sitter" function to keep a constant check on your baby.

If you set the radio in Baby Sitter mode, all the other traditional functions are disabled and the transceiver works only as baby monitor.

The baby sitter mode allows some specific functions for monitoring the baby:

- **Automatic transmission of the baby's radio (VOX)**: the baby's radio will automatically transmit when it picks up any noises. (e.g.: when the baby cries.)

- **Automatic Out of Range:** if the parent's radio moves too far away from the baby's radio, after 2 minutes an alert beep tone is emitted from the "parent" radio, advising you that the two radios are not in range anymore.
- **Manual Out of Range:** you can also manually check if the "baby" radio is in range by pressing the relative button on the parent's radio.
- **Talk to the baby:** normally at any moment, you can talk to the baby by just pressing the PTT button on the parent's radio.

Thanks to the **NEW "Talk Back" function**, if the baby's radio is transmitting for more than 20 seconds, the VOX Talk back function automatically stops the transmission permitting the parent to talk.

G6 XT in **Standard mode**, has all the functions of a traditional PMR446 transceiver, such as:

- **VOX function** for hand-free conversations
- **Out of Range function** to check if the radios are in range
- **Scan function** to find a busy channel
- **38 CTCSS tones** to create new private channels
- **Auto power Save function** for a reduction in consumption of up to 50%.

COMPLYING TO CE/99/05

COLOUR: BLACK

BLISTER BOX CONTENTS:

- 2 G6XT transceivers
- 2 600mAh 4,8V battery packs
- 1 double desktop charger
- 1 wall adaptor

G6 XT IS AVAILABLE WITH MOST OF MIDLAND 2 PIN ACCESSORIES.

Data

21/07/2009

Release

MAIN CHARACTERISTICS

- Frequency band: 446.00625 – 446.09375 MHz
- Aerial: 12.5KHz
- 8 PMR446 channels +40 channels with CTCSS tones
- 38 CTCSS tones
- Output power: 500mW ERP
- Coverage up to 4/5 km
- BABY SITTER function with 18 pre-set Baby Sitter channels
- OUT OF RANGE function
- In-built VOX function adjustable on 3 different levels + TALK BACK function
- 600mAh 4,8V battery pack or 4 AAA 1,5 V rechargeable/alkaline batteries
- LCD backlit alphanumeric Display
- Working temperature from -20° to +55°
- weight: 95 gr (without batteries)
- Dimensions: 58X98X28 mm
- MC CHG jack: 2 pin audio accessories/ wall charger